

MMX-8 - Microphone Mixer



Miniature universal audio mixer

- 8 mono channels, switchable mic/line
- Selection of 4 stereo channels
- 2 output level controls, 2 peak LEDs
- Supplied w/o battery

Tekniske data

| | |
|--------------------|----------------------------|
| No. of channels | : - |
| No. of inputs | : - |
| Mic input | : 5Â mV, 8 x 6.3 mm jack |
| Line input | : 50Â mV, 8 x 6.3 mm jack |
| CD input | : - |
| Phono input | : - |
| Tape (play) | : - |
| Aux input | : - |
| Insert input | : - |
| Effect return | : - |
| Master output | : 100Â mV, 2 x 6.3 mm jack |
| Record output | : - |
| Monitor output | : - |
| Booth output | : - |
| Aux output | : - |
| Insert output | : - |
| Effect send | : - |
| Control room | : - |
| Tape (rec) | : - |
| Headphones | : - |
| Gooseneck lamp | : - |
| WiFi | : - |
| USB | : - |
| Bluetooth | : - |
| Frequency range | : 20-20,000Â Hz |
| THD | : < 0.4% |
| S/N ratio | : 55 dB |
| Crosstalk | : - |
| Equalizer bass | : - |
| Equalizer midrange | : - |
| Equalizer treble | : - |
| equalizer | : - |
| Talkover | : - |
| Phantom power | : - |
| Crossfader | : - |

| | |
|--|--|
| Media player | : - |
| Amplifier | : - |
| Power supply | : 9Â V battery or via optional power supply PSS-600E |
| Mains voltage | : - |
| Mains frequency | : - |
| Power consumption, operation | : - |
| Operating voltage (possible alternative) | : - |
| Power supply (possible alternative) | : - |
| Admiss. ambient temp. | : 0-40 °C |
| Width | : 150 mm |
| Height | : 68 mm |
| Depth | : 115 mm |
| Rack spaces, RS | : - |
| Weight | : 550 g |