

MPX-622/SW - Stereo Mixer



6-channel stereo audio mixer,
particularly suitable for PA and DJ applications.

- 2 mono microphone channels with talkover switch and 2-way tone control
- 4 stereo input channels, switchable phono/line (channels 1 and 2) or line/line (channels 3 and 4)
- 1 stereo master output
- 1 stereo record output, independent of the master
- 3-way equalizer with centre click for master output and record output
- Pre-fader listening to each stereo input channel and the master output via adjustable stereo headphone output
- Switchable crossfader for crossfading between channels 1-4, any assignment possible
- Stereo LED level display

Tekniske data

No. of channels	: 6
No. of inputs	: 8
Mic input	: 1 \hat{A} mV, 2 x 6.3 mm jack
Line input	: 150 \hat{A} mV, 5 x RCA L/R
CD input	: 150 \hat{A} mV, 1 x RCA L/R
Phono input	: 3 \hat{A} mV, 2 x RCA L/R
Tape (play)	: -
Aux input	: -
Insert input	: -
Effect return	: -
Master output	: 0.775 \hat{A} V/600 \hat{A} Ohm, 1 x RCA L/R
Record output	: 0.775 \hat{A} V/600 \hat{A} Ohm, 1 x RCA L/R
Monitor output	: -
Booth output	: -
Aux output	: -
Insert output	: -
Effect send	: -
Control room	: -
Tape (rec)	: -
Headphones	: ? 8 \hat{A} Ohm, 1 x 6.3 mm jack
Gooseneck lamp	: -
WiFi	: -
USB	: -
Bluetooth	: -
Frequency range	: 20-20,000 Hz
THD	: 0.1%
S/N ratio	: 65 dB
Crosstalk	: -
Equalizer bass	: $\pm 10 \hat{A}$ dB/100 \hat{A} Hz
Equalizer midrange	: $\pm 10 \hat{A}$ dB/1 \hat{A} kHz
Equalizer treble	: $\pm 10 \hat{A}$ dB/10 \hat{A} kHz
equalizer	: -
Talkover	: -15 dB
Phantom power	: -
Crossfader	: yes

Media player	: -
Amplifier	: -
Power supply	: ∿ 230Â V/50Â Hz/10Â VA
Mains voltage	: ∼ 230 V
Mains frequency	: 50 Hz
Power consumption, operation	: 10 VA
Operating voltage (possible alternative)	: -
Power supply (possible alternative)	: -
Admiss. ambient temp.	: 0-40 °C
Width	: 482 mm
Height	: 89 mm
Depth	: 95 mm
Rack spaces, RS	: 2
Weight	: 2.4 kg