

MPR-1 - Microphone Pre-Amplifier



1-channel microphone preamplifier,
with switchable phantom power.

- 1 microphone input, XLR, bal. or 6.3 mm jack, bal.
- Gain control: up to 50 dB max.
- Clip LED
- 30 V phantom power, can be activated as required

Tekniske data

| | |
|-----------------------|---|
| Description | : microphone preamplifier |
| Frequency range | : 10-30,000 Hz |
| Control range | : - |
| Control frequencies | : - |
| Input signal | : 3.5 mV (XLR, bal.) 16 mV (jack, bal.) |
| Input sensitivity | : - |
| Input impedance | : 10 kOhm |
| Output signal | : 1 V |
| Output impedance | : - |
| Gain | : 50 dB (with bal. connection) 44 dB (with unbal. connection) |
| Phantom power | : - |
| Compression | : - |
| Gate ratio | : - |
| Crossover frequency | : - |
| High-pass filter | : - |
| Low cut | : - |
| Transmission ratio | : - |
| S/N ratio | : 58 dB |
| Channel separation | : - |
| THD | : 0.1% |
| Admiss. ambient temp. | : 0-40 °C |
| Power supply | : via encl. plug-in power supply |
| Dimensions | : 113 x 92 x 40 mm |
| Weight | : 345 g |
| Inputs | : 1 x XLR, 1 x 6.3 mm jack |
| Outputs | : 1 x XLR, 1 x 6.3 mm jack |
| Other features | : - |