

SA-160BT - Amplifier



Mini stereo amplifier, 2 x 30 W, with Bluetooth interface, NFC and remote control.

- Integrated hi-fi audio amplifier
- For speakers with an impedance of 8 Ohm
- Volume control with integrated source selector function, LED indicator
- Near Field Communication (NFC)
- Gold-plated speaker terminals
- 1 stereo input via RCA jacks L/R
- 1 line output via 3.5 mm stereo jack
- Fixed antenna
- Metal housing
- Power is provided via enclosed power supply

Tekniske data

| | |
|--|--------------------|
| Peak output power | : 2 x 60 W |
| Power rating | : 60 W |
| Power rating at 2 Ohm | : - |
| Power rating at 4 Ohm | : - |
| Power rating at 8 Ohm | : 2 x 30 W |
| Power rating at 16 Ohm | : - |
| Power rating at 100 V | : - |
| Power rating with 4 Ohm | : - |
| bridged operation | |
| Power rating with 8 Ohm | : - |
| bridged operation | |
| Output impedance | : - |
| Channels | : 2 |
| Zones | : - |
| Inputs | : 660Â mV/10Â kOhm |
| Attenuation factor | : - |
| Frequency range | : 20-20,000 Hz |
| Crossover network | : - |
| Crossover frequency | : - |
| Integrated limiter | : - |
| Equalizer bass | : - |
| Equalizer midrange | : - |
| Equalizer treble | : - |
| S/N ratio | : ? 99 dBA |
| Crosstalk attenuation | : - |
| THD | : - |
| Mains voltage | : - |
| Mains frequency | : - |
| Power consumption, operation | : - |
| Power consumption, standby | : - |
| Standby current | : 100 mA |
| Operating voltage (possible alternative) | : - |
| Power supply (possible alternative) | : - |
| Admiss. ambient temp. | : 0-40 °C |
| Width | : 150 mm |
| Height | : 49 mm |
| Depth | : 122 mm |



| | |
|-----------------|---|
| Rack spaces, RS | : - |
| Weight | : 610 g |
| Connections | : 1 x RCA L/R (line), 4 x spring-load. speaker term.(speakers) |