

TXS-631SET - Wireless Microphone



Multifrequency microphone system,
with UHF PLL technology.

- 1 pocket transmitter, 1 tie clip microphone, 1 receiver, 1 plug-in power supply
- True diversity system
- 80 selectable UHF channels (863-865 MHz)
- ACT function for transmitting the selected frequency to the pocket transmitter via infrared signal
- Auto-scan
- Volume and squelch controls
- Gain can be adjusted at the pocket transmitter
- Indication for channel, antenna A/B, ACT status and AF audio level (receiver), channel and battery status (pocket transmitter)
- Robust metal housing (receiver)

Licence-free in the EU.

Tekniske data

General information

| | |
|-------------------------|------------------------------|
| | : - |
| Description | : wireless microphone system |
| Carrier frequency range | : 863-865 MHz |
| Audio frequency range | : 50-18,000 Hz |
| Channels | : 1 |
| THD | : < 0.5% |
| Dynamic range | : 120 dB |
| RF S/N ratio | : 105 dB |
| Operating time | : - |
| Admiss. ambient temp. | : 0-40 °C |
| Power supply | : - |
| Dimensions | : - |
| Total weight | : - |
| Connections | : - |

Specifications transmitter

| | |
|--------------------------|---------------------------|
| | : - |
| Transmitting power | : < 10 mW |
| Operating range | : ? 30 m |
| Power supply transmitter | : 2 x 1.5 V batt. AA size |
| Width transmitter | : 62 mm |
| Height transmitter | : 105 mm |
| Depth transmitter | : 25 mm |
| Weight transmitter | : 88 g |
| Connections transmitter | : - |

Specifications receiver

| | |
|-----------------------|---|
| | : - |
| Audio signal receiver | : 350 mV/10 kOhm (jack) 25 mV/10 kOhm (XLR, bal.) |
| Power supply receiver | : via encl. plug-in power supply |
| Width receiver | : 152 mm |
| Height receiver | : 38 mm |
| Depth receiver | : 120 mm |
| Weight receiver | : 482 g |
| Connections receiver | : 1 x 6.3 mm jack, unbal. 1 x XLR, bal. |