

## MPR-1 - Microphone Pre-Amplifier



1-channel microphone preamplifier,  
with switchable phantom power.

- 1 microphone input, XLR, bal. or 6.3 mm jack, bal.
- Gain control: up to 50 dB max.
- Clip LED
- 30 V phantom power, can be activated as required

## Tekniske data

Description	: microphone preamplifier
Frequency range	: 10-30,000 Hz
Control range	: -
Control frequencies	: -
Input signal	: 3.5 mV (XLR, bal.)16 mV (jack, bal.)
Input sensitivity	: -
Input impedance	: 10 kOhm
Output signal	: 1 V
Output impedance	: -
Gain	: 50 dB (with bal. connection)44 dB (with unbal. connection)
Phantom power	: -
Compression	: -
Gate ratio	: -
Crossover frequency	: -
High-pass filter	: -
Low cut	: -
Transmission ratio	: -
S/N ratio	: 58 dB
Channel separation	: -
THD	: 0.1%
Admiss. ambient temp.	: 0-40 °C
Power supply	: via encl. plug-in power supply
Dimensions	: 113 x 92 x 40 mm
Weight	: 345 g
Inputs	: 1 x XLR, 1 x 6.3 mm jack
Outputs	: 1 x XLR, 1 x 6.3 mm jack
Other features	: -