

PA-1200 - PA Amplifier



4-zone mono PA mixing amplifier

- 1 x 120 W
- Silent operation due to fanless cooling concept
- Chime, continuous sound and wailing sound, automatic mute, chime can also be activated via external momentary push-button, 2-tone chime or 4-tone chime (selectable)
- Bass, treble and master controls, level display via LEDs
- 15 V phantom power for channels 2 and 3
- Insertions for various functions are available at option
- 482 mm (19") rack installation with mounting frame PA-1200RM, available at option
- Mains operation and 24 V emergency power operation

Tekniske data

| | |
|--|--|
| Peak output power | : 170 W |
| Power rating | : 120 W |
| Power rating at 2 Ohm | : - |
| Power rating at 4 Ohm | : - |
| Power rating at 8 Ohm | : - |
| Power rating at 16 Ohm | : - |
| Power rating at 100 V | : - |
| Power rating with 4 Ohm bridged operation | : - |
| Power rating with 8 Ohm bridged operation | : - |
| Output impedance | : - |
| Channels | : 5 |
| Zones | : 4 |
| Inputs | : 1.5 mV/600 Ohm (mic), 150 mV/47 kOhm (line), 1 mV/47 kOhm (phono) |
| Attenuation factor | : - |
| Frequency range | : 80-15,000 Hz |
| Crossover network | : - |
| Crossover frequency | : - |
| Integrated limiter | : - |
| Equalizer bass | : ± 10 dB/100 Hz |
| Equalizer midrange | : - |
| Equalizer treble | : ± 10 dB/10 kHz |
| S/N ratio | : ≥ 60 dB (mic), ≥ 70 dB (line) |
| Crosstalk attenuation | : - |
| THD | : $< 1\%$ |
| Mains voltage | : ≈ 230 V |
| Mains frequency | : 50 Hz |
| Power consumption, operation | : 280 VA |
| Power consumption, standby | : - |
| Standby current | : - |
| Operating voltage (possible alternative) | : DC 24 V |
| Power supply (possible alternative) | : DC 11 A |
| Admiss. ambient temp. | : 0-40 °C |

Width : 420 mm
Height : 122 mm
Depth : 350 mm





| | |
|-----------------|--|
| Rack spaces, RS | : - |
| Weight | : 12.28 kg |
| Connections | : 1 x 6.3 mm jack (mic input), 3 x XLR, bal. (mic/line inputs), 1 x RCA L + R (line input), 1 x RCA L + R (phono/line input), 1 x twin spring-loaded terminal (telephone input), 1 x twin spring-loaded terminal (tuner output), 1 x twin spri |