

DMP-130MIXBT - Audio Player/Mixer



MP3 player and microphone line mixer

With this unit combination, it is possible to mix 3 audio signal sources. The integrated MP3 player can be switched between SD card, USB port and Bluetooth receiver.

- For USB and SD storage media
- Alphanumeric display
- Repeat function
- Preprogrammed sound adjustments
- 3 input channels with level control (mic, aux/MP3, line)
- Aux input and microphone input via front panel connection
- 2-way tone control and level control for the master output
- Infrared remote control for MP3 player
- Blue backlit LCD
- 482 mm (19") rack installation

Tekniske data

| | |
|--|---|
| Description | : MP3 player and microphone line mixer |
| Media | : MP3, USB, SD, MMC |
| Frequency range | : 20-20,000 Hz |
| THD | : < 0.1% |
| Channel separation | : ? 60 dB |
| Dynamic range | : ? 96 dB |
| S/N ratio | : ? 70 dB |
| Output, analogue | : 2 V (XLR, bal.) 1 V (RCA) |
| Output, digital, U _{pp} | : - |
| Power supply | : ~; 230 V/50 Hz/20 VA |
| Mains voltage | : ~; 230 V |
| Mains frequency | : 50 Hz |
| Power consumption, operation | : 20 VA |
| Power consumption, standby | : - |
| Operating voltage (possible alternative) | : - |
| Power supply (possible alternative) | : - |
| Admiss. ambient temp. | : 0-40 °C |
| Dimensions | : 482 x 44 x 165 mm, 1 RS |
| Dim., player mech. | : - |
| Dim., control panel | : - |
| Weight | : 2.23 kg |
| Connections | : 1 x combo 6.3 mm/XLR (mic/line), 1 x 3.5 mm jack (aux in), 1 x RCA L/R (line in), 1 x RCA L/R (line out), |