

ATT100 - Travel Guide Walkie-Talkie



Tour guide transmitter

- 10+10 pre-programmed channels, channels 1-10 are transmitting with low power (operating range: approx. 200 m), channels 11-20 are transmitting with increased power (PMR446 standard: high operating range of up to 2 km)
- High battery capacity for continuous announcements of up to 6 hours
- Fully programmable (depending on the application)
- 3 different operating modes can be selected:
 - Continuous transmission
 - Voice control
 - Control via push-to-talk buttons (PTT)
- Matching the tour guide receiver ATR200
- Supplied with belt clip, lanyard

Licence-free, please refer to instruction manual on MONACOR's website.

Tekniske data

General information

	: -
Description	: 20-channel tour guide transmitter
Carrier frequency range	: 446.00625-446.1 MHz
Audio frequency range	: -
Channels	: 20
THD	: -
Dynamic range	: -
RF S/N ratio	: -
Operating time	: -
Admiss. ambient temp.	: -10 °C to +40 °C
Power supply	: -
Dimensions	: -
Total weight	: -
Connections	: -

Specifications transmitter

	: -
Transmitting power	: 10 mW/100 mW
Operating range	: 200 m/2 km
Power supply transmitter	: 1,200 mAh rech. lithium-ion batt.
Width transmitter	: 83 mm
Height transmitter	: 52 mm
Depth transmitter	: 27 mm
Weight transmitter	: 150 g
Connections transmitter	: 4-pole headset jack, DC charging socket

Specifications receiver	: -
Audio signal receiver	: -
Power supply receiver	: -
Width receiver	: -
Height receiver	: -
Depth receiver	: -
Weight receiver	: -
Connections receiver	: -