

## PA-1200IRD - Internet Radio



Internet radio, DAB+/FM RDS tuner insertion with USB interface, for PA mixing amplifier with insertion compartment.

- LAN or WLAN connection, WPS possible
- Detachable WLAN antenna
- Network Setup Wizard
- FM tuner with RDS
- 30 presets for your favourite radio stations (Internet radio 10x, DAB+ 10x, FM 10x)
- App control with the UNDOK? app
- USB storage media can be connected directly
- Media streaming of shared files shared on the network (UPnP server)
- Reproduction of MP3 and WAV files
- Display of file name
- Easy folder navigation
- Alphanumeric LCD
- Automatic switch-on after power failure (autostart)
- Storage of settings and operating modes
- Snooze function can be set
- Alarm function

## Tekniske data

Description	: Internet radio, FM RDS and DAB+ tuner, USB player
Media	: streaming, FM, DAB+, MP3, WAV, LAN/WLAN, USB
Frequency range	: -
THD	: -
Channel separation	: -
Dynamic range	: -
S/N ratio	: -
Output, analogue	: -
Output, digital, $U_{pp}$	: -
Power supply	: DC 17 V/500 mA
Mains voltage	: DC 17 V
Mains frequency	: -
Power consumption, operation	: -
Power consumption, standby	: -
Operating voltage (possible alternative)	: -
Power supply (possible alternative)	: -
Admiss. ambient temp.	: 0-40 °C
Dimensions	: 195 x 40 x 135 mm
Dim., player mech.	: -
Dim., control panel	: -
Weight	: 360 g
Connections	: 1 x RJ45 (LAN) 1 x IEC/coaxial plug for FM/DAB+ antenna 1 x SMA jack for WLAN antenna
Packing dimensions (W x H x L)	: 0.22 x 0.17 x 0.06 m
Gross weight	: 0.565 kg