

MEQ-115/SW - 15x2 Band Equalizer



Graphic equalizer

- 2-channel version, 2 x 15 frequency controls in 2/3 octave steps
- Switchable control range $\pm 6/\pm 12$ dB
- Peak LED
- Switchable low cut filter
- Master volume control
- Bypass switch and ground lift switch
- Frequency controls with centre click
- Inputs and outputs each via 2 x XLR and 2 x 6.3 mm jack

Tekniske data

Description	: graphic equalizer
Frequency range	: 20-20,000 Hz
Control range	: switchable $\pm 6/\pm 12$ dB
Control frequencies	: 2 x 25/40/63/100/160/250/400/630 Hz/ 1/1.6/2.5/4/6.3/10/16 kHz
Input signal	: 0.775 V
Input sensitivity	: -
Input impedance	: 50 kOhm
Output signal	: 0.775 V
Output impedance	: 600 Ohm
Gain	: -
Phantom power	: -
Compression	: -
Gate ratio	: -
Crossover frequency	: -
High-pass filter	: -
Low cut	: 20 Hz/-3 dB
Transmission ratio	: -
S/N ratio	: 66 dB
Channel separation	: -
THD	: < 0.1%
Admiss. ambient temp.	: 0-40 °C
Power supply	: \approx 230 V/50 Hz/10 VA
Dimensions	: 482 x 44.5 x 165 mm, 1 RS
Weight	: 2.5 kg
Inputs	: 2 x XLR, 2 x 6.3 mm jack
Outputs	: 2 x XLR, 2 x 6.3 mm jack
Other features	: -