

# ADP-DAO-0X2 - Dante Adaptor



Dante(r) analogue output adapter (2-channel)

- For connecting analogue audio line level devices (e.g. active speakers) to a Dante(r) audio network
- Adjustable signal level: +18/+4/0 dBu, 0/-10 dBV (via Dante(r) controller)
- Frequency range: 20-20,000 Hz
- Impedance: 150 kOhm (bal.), 75 kOhm (unbal.)
- Dynamic range: > 100 dB
- S/N ratio: > 100 dB
- THD: < 0.01%
- Sampling rates: 44.1/48/96 kHz, 24 bits
- Connections: 1 x RJ45, 2 x XLR plug

The brand Dante(r) as well as the Dante(r) software which may have been integrated into these products are licenced by Audinate Pty Ltd.

# Tekniske data

|                       |  |
|-----------------------|--|
| Description           | : Dante <sup>(r)</sup> analogue output adapter |
| Nominal value         | : -  |
| Type                  | : 2-channel                                    |
| Colour                | : black  |
| Material              | : -  |
| Suitable for          | : -  |
| Power supply          | : PoE  |
| Admiss. ambient temp. | : -  |
| Dimensions            | : -  |
| Length                | : -  |
| Mounting dimensions   | : -  |
| Weight                | : 165 g  |
| Connections           | : 1 x RJ45,<br>2 x 3-pole XLR plug             |
| Other features        | : -  |
| Packing unit          | : 1  |