

MPX-20USB - Stereo Mixer



3-channel stereo DJ mixer,
with USB interface. Plug and mix!

- Integrated USB audio interface (will be identified and addressed as an external sound card)
- Full-duplex USB port (allows for simultaneous recording and reproduction) for reproduction of digital audio data from a PC as well as for recording mixings onto a PC
- 1 microphone input channel
- 2 stereo input channels, switchable line/phono and USB/line/phono
- 1 stereo output channel (master)
- 1 stereo record output
- Pre-fader listening (CUE) to the stereo input channels via adjustable headphone output
- Crossfader
- LED level display
- Robust metal housing of compact size
- Power supply via USB interface or optional power supply with USB port

tools4music 04/2015

"Robust design, neat workmanship and great test results. The features of this unit certainly meet the requirements of practical applications."

delamar.de 11/2014

"The MPX-20USB from IMG Stage Line is a respectable mixer for two channels plus microphone which combines all the important features at a compact size. Great for DJs who concentrate on the essentials. Also suitable for anyone requiring a reliable second unit ... As a little bonus, there are in fact two headphone jacks. This space-saving mixer is able to crossfade two audio signals and well suited for home applications."

Tekniske data

No. of channels	: 4
No. of inputs	: 5
Mic input	: 1 mV, 1 x 6.3 mm jack
Line input	: 450 mV, 2 x RCA L/R
CD input	: -
Phono input	: 9 mV, 2 x RCA L/R
Tape (play)	: -
Aux input	: -
Insert input	: -
Effect return	: -
Master output	: 1 V, 1 x RCA L/R
Record output	: 1 V, 1 x RCA L/R
Monitor output	: -
Booth output	: -
Aux output	: -
Insert output	: -
Effect send	: -
Control room	: -
Tape (rec)	: -
Headphones	: 8 Ohm, 1 x 3.5 mm jack, 1 x 6.3 mm jack
Gooseneck lamp	: -
WiFi	: -
USB	: yes
Bluetooth	: -
Frequency range	: 20-20,000 Hz
THD	: 0.1%
S/N ratio	: 63 dB, unweighted
Crosstalk	: -
Equalizer bass	: -
Equalizer midrange	: -
Equalizer treble	: -
equalizer	: -
Talkover	: -
Phantom power	: -
Crossfader	: yes

Media player	: -
Amplifier	: -
Power supply	: DC 5 V/500 mA via USB interface
Mains voltage	: -
Mains frequency	: -
Power consumption, operation	: -
Operating voltage (possible alternative)	: DC 5 V
Power supply (possible alternative)	: DC 500 mA
Admiss. ambient temp.	: 0-40 °C
Width	: 150 mm
Height	: 70 mm
Depth	: 140 mm
Rack spaces, RS	: -
Weight	: 700 g